



	Controller Device	Condenser Units	Condenser Fans		Evap or Element Fans		Heat Extraction Fans		Elements		Lighting		Heat Lamp				TOTAL AMPS
		Amps	Qty	Amps	Qty	Amps	Qty	Amps	Qty	Amps	Type	Amps	Type	Watts	Qty	Amps	
<b>Regent</b>																	
RC6	Carel Easy	2.6			2	0.3	2	0.25			LED	0.23					3.3
RC9	Carel Easy	2.8			2	0.3	2	0.25			LED	0.37					3.7
RC12	Carel Easy	3.4			3	0.4	2	0.25			LED	0.51					4.5
RC15	Carel Easy	4.0			4	0.5	2	0.25			LED	0.65					5.4
RC18	Carel Easy	4.2			5	0.6	2	0.25			LED	0.75					5.8
RC24	Carel Easy	4.2			6	0.8	2	0.25			LED	1.03					6.2
RH6	Carel IR33				1	0.1			1	8.7	LED	0.23					9.1
RH9	Carel IR33				1	0.1			1	8.7	LED	0.37					9.2
RH12	Carel IR33				1	0.1			1	8.7	LED	0.51					9.4
RH15	Carel IR33				2	0.3			2	17.4	LED	0.65					18.3
RA6	N/A										LED	0.23					0.2
RA9	N/A										LED	0.37					0.4
RA12	N/A										LED	0.51					0.5
RA15	N/A										LED	0.65					0.7
RA18	N/A										LED	0.75					0.7
RA24	N/A										LED	1.03					1.0
<b>Lincoln</b>																	
LC6	Carel Easy	2.6			2	0.3	2	0.25			LED	0.23					3.3
LC9	Carel Easy	2.8			2	0.3	2	0.25			LED	0.37					3.7
LC12	Carel Easy	3.4			3	0.4	2	0.25			LED	0.51					4.5
LC15	Carel Easy	4.0			4	0.5	2	0.25			LED	0.65					5.4
LC18	Carel Easy	4.2			5	0.6	2	0.25			LED	0.75					5.8
LC24	Carel Easy	4.2			6	0.8	2	0.25			LED	1.03					6.2
LH6	Carel IR33				1	0.1			1	8.7	LED	0.23					9.1
LH9	Carel IR33				1	0.1			1	8.7	LED	0.37					9.2
LH12	Carel IR33				1	0.1			1	8.7	LED	0.51					9.4
LH15	Carel IR33				2	0.3			2	17.4	LED	0.65					18.3
LA6	N/A										LED	0.23					0.2
LA9	N/A										LED	0.37					0.4
LA12	N/A										LED	0.51					0.5
LA15	N/A										LED	0.65					0.7
LA18	N/A										LED	0.75					0.7
LA24	N/A										LED	1.03					1.0

	Controller Device	Condenser Units	Condenser Fans		Evap or Element Fans		Heat Extraction Fans		Elements		Lighting		Heat Lamp				TOTAL AMPS
		Amps	Qty	Amps	Qty	Amps	Qty	Amps	Qty	Amps	Type	Amps	Type	Watts	Qty	Amps	
<b>York</b>																	
YC6	Carel Easy	3.4			2	0.3	2	0.25			LED	0.29					4.2
YC9	Carel Easy	4.0			3	0.4	2	0.25			LED	0.47					5.1
YCO9 Impulse	Carel Easy	4.4			4	0.4	2	0.25	1	3.5	LED	0.37					9.0
YC12	Carel Easy	4.0			3	0.4	2	0.25			LED	0.64					5.3
YCO12 Impulse	Carel Easy	4.4			5	0.6	2	0.25	1	3.5	LED	0.51					9.2
YC15	Carel Easy	4.0			4	0.5	2	0.25			LED	0.82					5.6
YC18	Carel Easy	4.0			5	0.6	2	0.25			LED	0.93					5.8
YC24	Carel Easy	4.0			6	0.8	2	0.25			LED	1.28					6.3
YH6	Carel IR33				1	0.1			1	8.7	LED	0.35					9.2
YH9	Carel IR33				1	0.1			1	8.7	LED	0.56					9.4
YH12	Carel IR33				2	0.3			2	17.4	LED	0.77					18.5
YA6	N/A										LED	0.29					0.3
YA9	N/A										LED	0.47					0.5
YA12	N/A										LED	0.64					0.6
YA15	N/A										LED	0.82					0.8
YA18	N/A										LED	0.93					0.9
YA24	N/A										LED	1.28					1.3
<b>Tower</b>																	
TC6	Carel Easy	3.4			2	0.3	2	0.25			LED	0.56					4.5
TC9	Carel Easy	4.0			2	0.3	2	0.25			LED	0.77					5.3
TC12	Carel Easy	4.0			3	0.4	2	0.25			LED	0.98					5.6
TA6	N/A										LED	0.56					0.6
TA9	N/A										LED	0.77					0.8
TA12	N/A										LED	0.98					1.0

	Controller Device	Condenser Units	Condenser Fans		Evap or Element Fans		Heat Extraction Fans		Elements		Lighting		Heat Lamp				TOTAL AMPS
		Amps	Qty	Amps	Qty	Amps	Qty	Amps	Qty	Amps	Type	Amps	Type	Watts	Qty	Amps	
<b>Somerset</b>																	
SC12	Carel Easy	3.5			3	0.4					LED	0.26					4.1
SC15	Carel Easy	3.5			5	0.6					LED	0.33					4.5
SC18	Carel Easy	4.4			6	0.8					LED	0.40					5.5
SC21	Carel Easy	5.6			7	0.9					LED	0.46					6.9
SB12	EGO BM								1	8.7			Halogen	500	2	4.3	13.0
SB15	EGO BM								1	10.4			Halogen	500	3	6.5	17.0
SB18	EGO BM								1	13.0			Halogen	500	4	8.7	21.7
SB21	EGO BM								1	15.2			Halogen	500	5	10.9	26.1